

SMART PROBE SETUP GUIDE




USB Charging Port




SMART Probe Features:

- Food grade stainless steel pipe structure, waterproof
- grade IP67 (Dishwasher Safe)
- Bluetooth with transmission distance of 9m
- Food temperature measurement 0 C° 99 C°
- Grill/Oven temperature measurement 0 C° 276 C°
- No wires to contend with, perfect for Rotisserie Cooking
- Up to 4 probes can be connected to the App
- Fast charging via USB docking station
- · Magnet on docking station for convenience
- Fully charged in 2 minutes
- Capacitor enabled. No battery needed
- 24 hour standby. 4 hours operation time on full charge


Before we get started, make sure you have ready:



Apple iOS10 - iPhone 7/7+ / 10X/11/12/13



iPad Mini / iPad 2nd Gen iPad Pro & above



Android 4.4 - Android enabled devices including Samsung, etc.



OPERATING THE SMART PROBE



Oven Thermometer





- Charge your Smart Probe using a (5V) USB charger (Not included). Indicator light will change to green when fully charged. Remove probe from charging dock.
- Open BBiQ App and it will auto pair with your Smart Probe.
- You can monitor your food temp and your oven temp with the app. Up to 4 probes can be connected to the app.

Tips:

- Place the probe in the dock charger before each use. Charge for at least 2 minutes.
- The external (230V/240V) power supply is connected to the (5V) USB. The red light indicates charging in progress. The light will turn green when fully charged.
- Insert probe to safety notch. Do not insert probe past safety notch.
- Do not expose probe to temperatures exceeding 276 C°
- Keep probe clean by washing with soap & water or place in top rack of dishwasher.

Safety Notch (Insert to safety notch)

Food sensor